HP LaserJet Pro M402dne



Printing performance and robust security built for how you work. This capable printer finishes jobs faster and delivers comprehensive security to guard against threats.¹ Original HP Toner cartridges with JetIntelligence give you more pages.²

Print speed:Letter: Up to 40 ppm; First Page Out: As fast as 5.6 sec; As fast as 8.1 sec

 $\mbox{Print Resolution:} Black (best): Up to 4800 <math display="inline">\times$ 600 enhanced dpi, HP FastRes 1200

Print Technology Resolution: HP FastRes 1200, HP ProRes 1200, 600 dpi

Standard Connectivity: 1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network

Standard Memory:Standard: 256MB DRAM Mobile Printing Capability: HP ePrint; Apple AirPrint™:

MopriaTM-certified; Google Cloud Print 2.0; Mobile Apps **Paper Handling:** 100-sheet multipurpose Tray 1, 250sheet input Tray 2; 150-sheet output bin **Display:** 2-line backlit LCD graphic display













Fast printing. Strong protection.

- Grab pages and go—without waiting around. This printer wakes up and prints faster than the competition.¹
- Breeze through multipage documents with two-sided printing that's faster than the competition.¹
- Help keep printing safe from boot up to shutdown with security features that guard against complex threats.

More. Pages, Performance, and Protection.

- Get the most prints for your money—with Original HP High Yield Black Toner cartridges with JetIntelligence.²
- Count on consistent results at high speeds with precision black toner.
- Help ensure you're getting the authentic HP quality you paid for with innovative anti-fraud technology.
- Print right away with preinstalled toner cartridges. Replace them with optional high-yield cartridges.

Help save energy and easily manage tasks

- Help save energy with HP Auto-On/Auto-Off Technology.³
- Print using less energy than competitors—enhanced by Original HP Toner cartridges with JetIntelligence.⁴
- Make the most of your office space, with a printer that conveniently fits right into your work style.
- Easily manage devices and settings using HP Web Jetadmin with a suite of essential management features.⁵

Stay connected with easy mobile printing options

- Easily print from a variety of smartphones and tablets—generally no setup or apps required.⁶
- Easily set up, print, and share with built-in Ethernet networking.

¹ Based on HP internal testing of top three leading competitors' first page out from Sleep mode and duplex print speed completed 8/2015. Subject to device settings. Actual results may vary. For details see http://www.hp.com/go/Ljclaims. Automatic two-sided printing not available for the HP Laser-let Pro M402n.² Based on carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared with HP 26K Original HP Laser-let Toner Carridge yields for HP 80X compared yields for the releading competitors as of 8/2015. Actual results may vary. For details see http://www.hp.com/go/Ljclaims ⁵ HP Web Jetadmin is free and available for download at http://www.hp.com/go/Webjetadmin ⁶ Wireless operations are compatible with 2.4 GHz operations only. App or software and HP e/int account registration may also be required. Some features require purchase of an optional accessory. Learn more at http://www.hp.com/go/mobileprinting

HP LaserJet Pro M402dne Specifications Table

Print Speed	Letter: Up to 40 ppm black; ⁴ First Page Out: As fast as 5.6 sec black; ⁵	Compatible Network Operating Systems	Windows OS compatible with In-Box Driver: Windows Server 2003/2003 R2 32-bit (SP1/SP2) Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2008 R2 64-bit (SP1) Standard/Enterprise (+ Cluster & Terminal Services), Windows Server 2008 R2 64-bit (SP1) Standard/Enterprise (+ Cluster & Terminal Services), Windows OS compatible with Universal Print Driver (UPD) or Product-Specific drivers from HP.com: Windows Server 2003 R2003 R2 32-64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2003/2008 R2 32-64-bit (SP1/SP2) Standard/Enterprise/Datacenter (+ Cluster & Terminal Services), Windows Server 2012/2012 R2 64-bit Standard/Foundation/Essentials/Datacenter (+ Cluster & Terminal Services), MS Windows Server 2012 R2 Terminal Services: Citrix XenDap 7.5, Citrix XenDesktop 7.0, Citrix XenDesktop 7.0, Citrix XenDesktop 7.5, SW Windows Server 2008 R2 SP1 Terminal Services; Citrix XenDesktop 7.0, Citrix XenDesktop 7.6, Citrix XenDesktop 7.5, SW Windows Server 2008 R2 SP1 Terminal Services; Citrix XenDesktop 5.0, Citrix XenDesktop 5.6, Citrix XenDps 5.6, Citrix XenDps 6.0, Citrix XenDesktop 7.5, SW Windows Server 2008 R2 SP1 Terminal Services; Citrix XenDps 6.0, Citrix XenDesktop 7.5, SW Windows Server 2003 BE Terminal Services; Citrix XenDps 6.0, Citrix XenDps 5.0, Citrix Xe	
Print Resolution	Black (best): Up to 4800 x 600 enhanced dpi, HP FastRes 1200			
Print Technology	Laser			
Print Resolution Technologies	HP FastRes 1200, HP ProRes 1200, 600 dpi			
Print Cartridges Number	1 (black)			
Standard Print languages	HP PCL 5, HP PCL 6, HP postscript level 3 emulation, direct PDF (v 1.7) printing, URF, PCLM, PWG			
Printer Smart Software Features	Auto-duplex printing, N-up printing, collation, HP ePrint, Apple AirPrint™, Google Cloud, Print Mopria-certified, Instant-on Technology, HP Auto-On/Auto-Off technology, JetIntelligence Cartridge Technology, Job Storage with PM printing			
Printer Management	Printer Administrator Resource Kit (Driver Configuration Utility, Driver Deployment Utility, Managed Printing Administrator); HP Web JetAdmin Software; HP Proxy Agent Software; HP Imaging and Printing Security Center; HP Utility (Mac); HP Device Toolbox			
Standard Connectivity	1 Hi-Speed USB 2.0; 1 Host USB; 1 Gigabit Ethernet 10/100/1000T network			
Network Capabilities	Yes, via built-in 10/100/1000Base-TX Ethernet, Gigabit; Auto-crossover Ethernet; Authentication via 802.1X			
Network Ready	Standard (built-in Gigabit Ethernet)			
Wireless Capability	No			
Mobile Printing Capability	HP ePrint; Apple AirPrint™; Mopria™-certified; Google Cloud Print 2.0; Mobile Apps	Minimum System Requirements	PC: Windows 10 (32-bit/64-bit), Windows 8.1 (32-bit/64-bit), Windows 8 (32-bit/64-bit),	
Memory	Standard: 256MB DRAM; Maximum: 256MB DRAM		Windows 7 (32-bit/64-bit): 1 GHz processor, 1 GB RAM (32-bit) or 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM on Internet, USB on Network port; Windows Vista (32-bit): 1 GHz 32-bit (x86) processor, 1 GB RAM (32-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows XP (32-bit) SP2: Pentium 233 MHz processor, 51 ZM BRAM 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; Windows Server 2003 (32-bit) (SP1 or greater), Windows Server 2003 R2 (32-bit), Windows Server 2003 (32-bit) (SP1 or greater), Windows Server 2003 R2 (32-bit), Windows Server 2008 (32-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit), V00 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port Windows Server 2008 (64-bit) (SP1 or greater), Windows Server 2008 R2 (64-bit), Windows Server 2008 R2 (64-bit) (SP1): 1 GHz 64-bit (646) Processor, 2 GB RAM (64-bit), 400 MB available hard disk space, CD/DVD-ROM or Internet, USB or Network port; MAC OS X 10.8 Mountain Lion; OS X 10.9 Mavericks; OS X 10.10 Yosernite; Internet; USB; 1 GB available hard disk space; OS compatible hardware (For OS hardware requirements see http://www.apple.com)	
Processor Speed	1200 MHz / Hard disk: None			
Duty Cycle	Monthly, letter: Up to 80,000 pages ⁶			
Recommended Monthly Page Volume				
	/ 50 10 4000			
Media Types Supported	Paper (plain, EcoFFICIENT, light, heavy, bond, colored, letterhead, preprinted, prepunched, recycled, rough); envelopes; labels; transparencies			
Media Weight Supported	Tray 1: 16 to 46.6 lb; Tray 2 and Optional 550-sheet Tray 3: 16 to 32 lb			
Media Sizes Supported	Tray 1: Letter, Legal, Executive, Envelope #10, Envelope Monarch, Custom size 4 x 6 in, 5 x 8 in, 10 x 15 in statement; Tray 2 & Tray 3: Letter, Legal, Executive, Custom Size, 5 x 8 in, statement			
Media Sizes Custom	Tray 1: 3 x 5 to 8.5 x 14 in; Tray 2 and 3: 4.13 x 5.85 to 8.5 x 14 in	Power	Power Supply Type: Internal (built-in) power supply; Power Requirements: 110-volt input voltage: 110 to 127 VAC (+/ - 10%), 50/60 Hz (+/ - 2 Hz); 220-volt input voltage: 220 to 240 V/ (+/ - 10%), 50/60 Hz (+/ - 212) (Not dual voltage, power supply varies by part number with #option code identifier); Power Consumption: 591 watts (Active Printing), 6.1 watts (Ready), 2 watts (Sleep), 0.6 watts (Auto-On/Auto-Off, via USB connectivity), 0.1 watts (Shutdown or Off) ¹⁴	
Paper Handling	100-sheet multipurpose Tray 1, 250-sheet input Tray 2; 150-sheet output bin; Duplex Options : Automatic(standard); Envelope Feeder : No; Standard Paper Trays : 2; Input Capacities : Up to 350 sheets (Tray 1: up to 100 sheets; Tray 2: up to 250 sheets); Output Capacities : Up to 150 sheets; Up to 10 envelopes; Up to 75 sheets			
What's in the box	CSJ91A HP Laser jet Pro M402dne; Preinstalled HP 26A Black Laser jet Toner Cartridge (~3100 pages), Getting Started Guide; Setup Poster; Support Flyer; Warranty Guide; Printer documentation and software on CD-ROM; Power cord	Acoustics	Acoustic Power Emissions (active): 6.8 B(A); Acoustic Power Emissions (ready): Inaudible; Acoustic Pressure Emissions (active): 54 dB(A); Acoustic Pressure Emissions (ready): Inaudible	
Replacement Cartridges	HP 26A Black LaserJet Toner Cartridge (~3100 pages), CF226A; HP 26X Black LaserJet Toner Cartridge (~9000 pages), CF226X; HP 26XC Black LaserJet Toner Cartridge, CF226XC ¹	Operating Environment	Operating Temperature Range: 59 to 90.5%; Recommended Operating Temperature: 63.5 to 77%; Storage Temperature Range: -4 to 104%; Non-Operating Humidity Range: 10 to 90% R Operating Humidity Range: 10 to 80% RH; Recommended Humidity Operating Range: 30 to	
Product Dimensions	W x D x H : 15 x 14.06 x 8.5 in ² ; Maximum : 15 x 25 x 9.5 in		70% RH	
Product Weight	18.92 lb	Security Management	Embedded Web Server: password-protection, secure browsing via SSL/TLS; Network: enable/disable network ports and features, SNMPV1 & SNMPV2 community password change; HP ePrint: HTTPS with certificate validation, HTTP Basic Access Authentication, SASL authentication; Firewall and ACL; SNMPV3, 802.1X, Secure Boot	
Warranty Features	One-year warranty, return to HP Authorized Service Provider			
Energy Efficiency Compliance	ENERGY STAR® certified; Blue Angel; EPEAT® Silver			
Control Panel	2-line backlit LCD graphic display; Buttons (OK, Menu, Cancel, Back); LED indicator lights (Attention, Ready)	Accessories HP Service and Support Options	HP Laser Jet 550-sheet Feeder/Tray D9P29A; HP v222w 166B Mini USB Drive P0RB1AA U8TMSE HP 3 year Next Business Day Exchange Laser Jet M402 Service; U8TM2E HP 3 year Next Business Day Laser Jet M402 Hardware Support; U8TM3E HP 4 year Next Business Day Laser Jet M402 Hardware Support; U8TM4E HP 5 year Next Business Day Laser Jet M402 Hardware Support; U8TM7E HP 1 year Post Warranty Next Business Day Laser Jet M402 Hardware Support; H3110E HP Network Install Inkjet/Personal Laser Jet Service	
Display Description	2-line backlit LCD graphic display			
Software Included	For Windows 7: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, HP Device Experience (DXP), HP Update, HP Device Toolbox, HP Printer Status and Alerts, HP Product Improvement			
	Study, Reconfigure your HP Device; Warranty and Legal Guide, User Guide; For Windows 8+ HP Software Installer/Uninstaller, HP DC-6 Printer Driver, HP Device Experience (DXP), Warranty and Legal Guide, User Guide, Reconfigure your HP Device; For Windows XP, Windows Vista and associated servers: HP Software Installer/Uninstaller, HP PCL 6 Printer Driver, Warranty and Legal Guide, User Guide; For Mac OS: Welcome Screen (Directs users to http://www.HP.com or	Learn more at hp.com		
	OS App Source for LaserJet Software)			
Fonts and Typefaces	84 scalable TrueType fonts			
Compatible Operating Systems	Windows OS compatible with In-Box Driver: Windows XP SP3 all 32-bit editions (XP Home, XP Pro, etc), Windows Sta all 32-bit editions (Horne Basic, Premium, Professional, etc), Windows 7 all 32 & 64-bit editions (Windows 8/8,1 all 32 & 64-bit editions (kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 7 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 7 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 7 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 7 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 7 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 64-bit editors (Kwotending RT OS for Tablets), Windows 10 all 32 & 61-bit editions (Kwotending RT OS for Tablets), Windows 10 all 32 & 10, 10 NUK WINT (12, 12, 13, 13, 13, 13, 10 Windows 10, 10, 10, 10, 13, 14, 15, 17, 595 EURORA (17, 18, 19, 20), LINUX MINT (13, 14, 15, 17, 17, 595 EURORA (17, 18, 19, 20), LINUX MINT (13, 14, 15, 16, 17, 595 EURORA (17, 18, 19, 20), LINUX MINT (13, 14			

¹ Declared yield value in accordance with ISO/IEC 19752. Actual yields vary considerably based on images printed and other factors. For more information, visit http://www.hp.com/go/learnaboutsupplies² Without optional 550-sheet tray; Dimensions with optional 550-sheet tray; 15 x 14.06 x 13.58 in (381 x 357 x 345 mm)³ Job Storage feature requires a purchase of separate USB flash drive with a minimum of 16 GB capacity.⁴ Measured using ISO/IEC 24734, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.⁵ Measured using ISO/IEC 17629, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.⁶ Measured using ISO/IEC 17629, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Evant speed varies depending on the system configuration, software application, driver, and document complexity.⁶ Measured using ISO/IEC 17629, excludes first set of test documents for more information see http://www.hp.com/go/printerclaims. Evant speed varies depending on the system configuration, software application, driver, and document complexity.⁶ Duty cycle is defined as the maximum number of pages per month of image doubut. This value provides a comparison of product robustness in relation to other HP Laser. Jet or HP Color Laser. Jet devices, and enables appropriate deployment of printers and MFPs to satisfy the demands of connected individuals or groups.⁷ HP recommends that the number of pages per month be within the

stated range for optimum device performance, based on factors including supplies replacement intervals and device life over an extended warranty period.⁸ HP SureSupply alerts you when your print cartridge is running low and helps you purchase online or locally through HP or a participating retailer. For more information, visit http://www.hp.com/ga/SureSupply; only available with Original HP supplies; Internet access required.⁹ Not all "Compatible Operating Systems" are supported with inbox software; Full solution software; Full solution; Full ISO/IEC 24734 Feature Performance Test, excludes first set of test documents. For more information see http://www.hp.com/go/printerclaims. Exact speed varies depending on the system configuration, software application, driver, and document complexity.¹⁴ Powe requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This will damage the printer and void the product warranty.¹⁵ Typical Electricity Consumption (TEC) rating represents the typical electricity consumed by a product during 1 week, measured in kilowatt-hours (kWh).

© Copyright 2016 HP Development Company, L.P. The information contained herein is subject to change without notice. The only warranties for HP products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. HP shall not be liable for technical or editorial errors or omissions contained herein. ENERGY STAR and the ENERGY STAR logo are registered U.S. marks. Windows is a registered trademark of Microsoft Corporation. AirPrint, iPad, iPhone, and iPod touch are trademarks of Apple Inc., registered in the U.S. and other countries



OS: UNIX9